



Notes:

- The control center cabinet at the inside and outside foundation joints shall be sealed with a silicone sealant
- For alternate method of service cable entering safety switch see Standard SE-5.
- When 200 amp or greater service is required, service shall enter meter base at right bottom.
- No other conductors shall be run in the same conduit with electrical service cable.
- Local power utility company will install service power utility cable from their power source to the junction box and make required splices to the service cable coiled in the junction box.
- This standard is applicable for all electrical services other than 480Y/277. For 480Y/277 service, see Standard SE-9.

ELECTRICAL SERVICE DETAILS SIGN AND LIGHTING INSTALLATIONS