



Bolt projection as required by signal pole manufacturer, however distance between bottom of base plate and top of pedestal shall be less than or equal to twice the diameter of anchor bolt but shall not be greater than 3".

Square or hex nuts under base casting serve as a means of leveling or raking pole.

All conduits as specified on plans. In addition 1/2" conduit required for ground wire. 2 - 2" PVC heavy wall conduits required for future use. Note that additional spare conduits may be required by plans

**Notes:**

Anchor bolts and bolt pattern shall be furnished with pole. Pole shall be centered on foundation.

Each foundation shall be permanently marked to indicate all sides from which conduits pass. This mark shall be made with a trowel when finishing the concrete and shall be 1/4" deep and 4" to 6" long. Locations of empty conduits shall have an additional 2" long mark made perpendicular to and centered on this marking.

When foundation extends 4" above finished grade all edges shall be chamfered 3/4".

Grounding bushings shall be installed on each end of metal conduits. Empty conduits shall be plugged to prevent moisture and rodent entry.

Bell ends shall be installed on each end of PVC conduits. Empty conduits shall be plugged to prevent moisture and rodent entry.

Voids remaining after conductors exit or enter bell ends or bushings of conduits shall be sealed with silicone to prevent moisture and rodent entry.

No mortar, grout, or concrete shall be placed between bottom of base plate and top of pedestal.

**SIGNAL POLE FOUNDATION  
INSTALLATION DETAILS**

VIRGINIA DEPARTMENT OF TRANSPORTATION