

RURAL EXAMPLE

20 FT PAVEMENT WIDTH
(DESIGN SOFTWARE - 1 LANE AT 10 FT)

$V_D = 50$ MPH $R = 1000$ FT
 $W_n = 10$ FT $rg = 0.50$
 $E = 7.6$ (7.6% PER 802.40)

$U = u + R - \sqrt{R^2 - L^2}$
 $U = 8.0 + 1000 - \sqrt{(1000)^2 - (20)^2}$
 $U = 8.20002$

$F_A = \sqrt{R^2 + A(2L + A)} - R$
 $F_A = \sqrt{(1000)^2 + 4[2(20) + 4]} - 1000$
 $F_A = .087996$

$Z = (V_D / \sqrt{R})$
 $Z = (50 / \sqrt{1000})$
 $Z = 1.58$

$W_C = N(U + C) + F_A + Z$
 $W_C = 2(8.20002 + 2) + 0.087996 + 1.58$
 $W_C = 22.0680$

$w = W_C - 2W_n = 22.0680 - 2(10) = 2.1$

($R < 2865$ & $w > 2$ THEREFORE WIDENING IS REQUIRED)
 $L_r = [E n_1 (W_n + w/2) / rg] b_w$
 $L_r = [7.6(1)(10 + 2.1/2) / 0.50] 1$
 $L_r = 7.6 (11.05) / 0.50$
 $L_r = 167.96$

RURAL EXAMPLE

72 FT PAVEMENT WIDTH
(DESIGN SOFTWARE - 3 LANES AT 12 FT)

$V_D = 40$ MPH $R = 500$ FT
 $W_n = 12$ FT $rg = 0.58$
 $E = 8.0$ (8% PER PAGE 802.38)

$U = u + R - \sqrt{R^2 - L^2}$
 $U = 8.0 + 500 - \sqrt{(500)^2 - (20)^2}$
 $U = 8.4002$

$F_A = \sqrt{R^2 + A(2L + A)} - R$
 $F_A = \sqrt{(500)^2 + 4[2(20) + 4]} - 500$
 $F_A = .1760$

$Z = (V_D / \sqrt{R})$
 $Z = (40 / \sqrt{500})$
 $Z = 1.7885$

$W_C = 2(U + C) + F_A + Z$
 $W_C = 2(8.4002 + 3.0) + .1760 + 1.7885$
 $W_C = 24.7651$

$w = W_C - 2W_n = 24.7651 - 2(12) = 0.7651(0.8)$

FOR 72' PAVEMENT WIDTH

$w = 3(0.8) = 2.4$

($R < 881$ & $w > 2$ THEREFORE WIDENING IS REQUIRED)

$L_r = [E n_1 (W_n + w/3) / rg] b_w$
 $L_r = [8 (3) (12 + 2.4/3) / 0.58] 0.6667$
 $L_r = (307.2 / 0.58) 0.6667$
 $L_r = 353.1211$

OR

$L_r = MCE(W_n + w/N) / rg$
 $L_r = 2 [8(12 + 4.5/3) / 0.58]$
 $L_r = 2 (102.4 / 0.58)$
 $L_r = 353.1034$

URBAN EXAMPLES

24 FT PAVEMENT WIDTH
(DESIGN SOFTWARE - 1 LANE AT 12 FT)

$V_D = 40$ MPH $R = 600$ FT
 $W_n = 12$ FT $rg = 0.58$
 $E = 4.0$ (4% PER PAGE 802.29)

$L_r = (W_n n_1 E / rg) b_w$
 $L_r = [12(1)(4) / 0.58] 1.00$
 $L_r = (48 / 0.58)$
 $L_r = 82.7586$

66 FT PAVEMENT WIDTH
(DESIGN SOFTWARE - 3 LANES AT 11 FT)

$V_D = 40$ MPH $R = 600$ FT
 $W_n = 11$ FT $rg = 0.58$
 $E = 4.0$ (4% PER PAGE 802.29)

$L_r = b_w (W_n n_1 E / rg)$
 $L_r = 0.6667 [11(3)(4) / 0.58]$
 $L_r = 0.6667 (132 / 0.58)$
 $L_r = 151.7317$

OR

$L_r = M (E W_n / rg)$
 $L_r = 2 [4(11) / 0.58]$
 $L_r = 2 (44 / 0.58)$
 $L_r = 151.7241$

CALCULATED TC-5.01 EXAMPLES